



**Product suitable for areas
 Internal. Optimal installation in
 4X2 walk-through box**

1º - Pass the power network wires through the central hole of the BASE.

2 - Secure the base to the PASSAGE BOX with the screws that come with the product. Be careful when fixing the BASE make sure the SPRINGS are up.

3rd - Make the electrical connection. Check if the product voltage is in accordance with the building tension.
 4th - Fit the FRONT into the BASE, which will be attached by the SPRINGS.

Para a troca do LED
 1º - Retire a FRENTE do produto
 2º Desrosqueie os dois PARAFUSOS fixados na parte superior da peça.
 For the change of the LED 1st - Remove the FRONT of the product
 2nd Unscrew the two SCREWS fixed at the top of the piece.

3rd - Release the REFLECTOR and take off the Led. remove the FRONT of the product
 4º Remove the film from the new LED and paste again.
*****Do not glue the LED with another type of glue.**

ML-2298 2" x 4 6/8" x 3 1/8" 120V Power: 6W Weight: 2.84 lbs
 ML-2299 2" x 4 6/8" x 3 1/8" 120V Power: 6W Weight: 2.84 lbs

Attention

Follow the instructions to ensure proper and safe operation. We recommend that the installation be done by a qualified professional. Recessed ceiling installation requires rigid support point attachment and special installations require special attachment.

Important

Lamps, transformers, and reactors are not included with the product except as noted. Failure to follow the instructions in the manual could result in accidents and loss of warranty. Do not adjust springs and brackets unless otherwise indicated.
 Warranty: 1 year for product and 5 years for Led and Driver.

Cleaning and Maintenance

Before any action turn off the electric current. Clean only with water dampened flannel, never use chemicals or abrasives. The materials that make up the product are non-toxic.